




A company of SIM Tech

# **SIM868\_GNSS\_AGPS\_Application Note\_V1.00**



SIMCOM CONFIDENTIAL FILE

<b>Document Title:</b>	SIM868_GNSS_AGPS_Application Note
<b>Version:</b>	1.00
<b>Date:</b>	2017-01-03
<b>Status:</b>	Released
<b>Document Control ID:</b>	SIM868_GNSS_AGPS_Application Note_V1.00

### General Notes

SIMCom offers this information as a service to its customers, to support application and engineering efforts that use the products designed by SIMCom. The information provided is based upon requirements specifically provided to SIMCom by the customers. SIMCom has not undertaken any independent search for additional relevant information, including any information that may be in the customer's possession. Furthermore, system validation of this product designed by SIMCom within a larger electronic system remains the responsibility of the customer or the customer's system integrator. All specifications supplied herein are subject to change.

### Copyright

This document contains proprietary technical information which is the property of SIMCom Limited., copying of this document and giving it to others and the using or communication of the contents thereof, are forbidden without express authority. Offenders are liable to the payment of damages. All rights reserved in the event of grant of a patent or the registration of a utility model or design. All specification supplied herein are subject to change without notice at any time.

*Copyright © Shanghai SIMCom Wireless Solutions Ltd. 2017*

## Contents

<b>1</b>	<b>Overview .....</b>	<b>6</b>
<b>2</b>	<b>EPO orbit prediction.....</b>	<b>7</b>
2.1	EPO operation requirement.....	7
2.2	EPO orbit prediction process.....	7
2.3	EPO operation sample.....	7
<b>3</b>	<b>SimFastFix function.....</b>	<b>10</b>
3.1	SimFastFix function requirement.....	10
3.2	SimFastFix function process.....	10
3.3	SimFastFix function sample.....	10
	<b>Appendix.....</b>	<b>13</b>
A	Related documents.....	13
B	Terms and Abbreviations .....	13

## Version history

Date	Version	Description of change	Author
2017-01-03	1.00	New version	Xiping.li

## Scope

This document is a reference for SIM868 GSM+GPS+GLONASS module which is based on MTK platform.

This document does not provide information about NMEA\_0183 protocol.


## 1 OVERVIEW

SIM868 supports 3 kinds of fixing technologies,

- 1) GNSS EASY self-generated orbit prediction, off-line mode.
- 2) GNSS EPO orbit prediction, TTFF could be 10s minimum in open sky.
- 3) SimFastFix function, TTFF could be 5s minimum in open sky.

**Notice:**

- 1) *EASY technology is enabled in GNSS standard alone mode by default; first cold start will not help, after warm start, TTFF will be reduced to 15s around. EASY technology only takes 3 days ephemeris data from now on.*
- 2) *EPO and SimFastFix technologies require GPS UART interface to be connected to GSM UART2 interface as below. These two technologies will take effect immediately after cold start.*



## 2 EPO ORBIT PREDICTION

### 2.1 EPO operation requirement

- 1) UTC time is important before EPO data operation, because module will validate EPO data expiration date based on RTC time. You can get real time clock by following ways.
  - a) Network time from cell tower by AT command AT+CLTS=1/AT&W. Next reboot module will get real time clock from network operator if it is supported, and update it to local RTC time which could be shown by command "AT+CCLK?".
  - b) Network time from NTP server. This will require GPRS service available. And enable SAPBR protocol for NTP function; please refer to document "SIM800 Series NTP Application Note.pdf".
- 2) EPO file from server. SIMCom provide FTP server for EPO file update regularly. Also, user can get MTK EPO file from different FTP or HTTP server. SIMCom FTP server provides EPO files for different days, and updates it every single day.

FTP server address is: <ftp://116.247.119.165>, username is "customer" and password is "111111".

### 2.2 EPO orbit prediction process

- 1) Make sure module attach GPRS service;
- 2) Synchronize network UTC time;
- 3) Get EPO file from SIMCom ftp server and save it to module file system;
- 4) Enable GNSS and pass EPO file to GNSS engine;
- 5) Read GNSS fixing location from GNSS engine.

**Notice:**

*EPO file should be re-installed after GNSS cold start.*

### 2.3 EPO operation sample

In the "Grammar" columns of following tables, input of AT commands are in black, module return values are in blue.

Grammar	Description
AT+SAPBR=3,1,"CONTYPE","GPRS" OK	Set bearer parameter
AT+SAPBR=3,1,"APN","3GNET" OK	Set bearer context
AT+SAPBR=1,1	Active bearer context

OK	
AT+SAPBR=2,1 +SAPBR: 1,1,"10.73.119.61"	Read bearer parameter
OK	
AT+CNTPCID=1 OK	Set GPRS Bearer Profile's ID
AT+CNTTP? +CNTTP: 202.120.2.101.0	Read NTP server and time zone parameter
OK	
AT+CNTTP OK +CNTTP: 1	Synchronize Network Time to local
AT+CCLK? +CCLK: "16/12/15.11:02:32+0"	Read local time
OK	
AT+FTPSERV="116.247.119.165" OK	Set FTP server address
AT+FTPUN="customer" OK	Set FTP user name
AT+FTPPW="111111" OK	Set FTP password
AT+FTPGETNAME="MTK3.EPO" OK	Set download file name
AT+FTPGETPATH="/" OK	Set Download file path
AT+FTPEXTGET=1 OK +FTPEXTGET: 1,0	Download data to local buffer
AT+FTPEXTGET=4,"epo" +FTPEXTGET: 2,27648 OK	save data to local disk as EPO file
AT+FSLC=C:\User\ Epo OK	List Directories/Files
AT+CGNSCHK=3,1 +CGNSCHK: 3,1,27648,61	Check EPO file size and validation

OK	
AT+CGNSPWR=1 OK	Power on GPS
AT+CGNSAID=31,1,1 OK  +CGNSAID: OK	Send EPO file to GPS  EPO file has been written to GNSS buffer successfully
AT+CGNSINF +CGNSINF: 1,1,20161215045641.000,31.221303,121.355042 ,71.900,0.00,45.1,1,,1.0,1.3,0.8,,10,10,,,36,,  OK	Read GPS location data

SIMCOM CONFIDENTIAL FILE



### 3 SIMFASTFIX FUNCTION

#### 3.1 SimFastFix function requirement

There have three necessary requirements for SimFastFix function.

- 1) UTC time, as mentioned in section 2 above.
- 2) Reference location. Module supports GSM LBS function, this function can feed this reference location to SimFastFix. Also, user can give reference location info by manual with AT command.
- 3) EPO data.

#### 3.2 SimFastFix function process

- 1) Make sure module attach GPRS service;
- 2) Synchronize network UTC time;
- 3) Feed reference location longitude/latitude by LBS function or by manual (AT+CRFLOC);
- 4) Get EPO file from SIMCom ftp server and save it to module file system;
- 5) Enable GNSS and pass EPO file to GNSS engine;
- 6) Read GNSS fixing location from GNSS engine.

*Notice:*

- a) *EPO file should be re-installed after GNSS cold start.*
- b) *Reference location buffer will be cleared after command AT+CGNSAID. So this location info should be fresh and feed again (by command AT+CLBS or AT+CRFLOC) every time before GNSAID action.*

#### 3.3 SimFastFix function sample

In the "Grammar" columns of following tables, input of AT commands are in black, module return values are in blue.

Grammar	Description
AT+SAPBR=3,1,"CONTYPE","GPRS" OK	Set bearer parameter
AT+SAPBR=3,1,"APN","3GNET" OK	Set bearer context
AT+SAPBR=1,1 OK	Active bearer context
AT+SAPBR=2,1 +SAPBR: 1,1,"10.73.119.61" OK	Read bearer parameter
AT+CNTPCID=1 OK	Set GPRS Bearer Profile's ID

<p>AT+CNTP? +CNTP: 202.120.2.101,0</p> <p>OK</p>	<p>Read NTP server and time zone parameter</p>
<p>AT+CNTP OK +CNTP: 1</p>	<p>Synchronize Network Time to local</p>
<p>AT+CCLK? +CCLK: "16/12/15,11:02:32+0"</p> <p>OK</p>	<p>Read local time</p>
<p>AT+CLBS=1,1 +CLBS: 0,121.359977,31.220240,550</p> <p>OK</p>	<p>Require LBS info, and module will update this info for reference location automatically.</p> <p>Or here feed reference location by command below: AT+CRFLOC="131.220240,21.359977"</p>
<p>AT+FTPSERV="116.247.119.165" OK</p>	<p>Set FTP server address</p>
<p>AT+FTPUN="customer" OK</p>	<p>Set FTP user name</p>
<p>AT+FTPPW="111111" OK</p>	<p>Set FTP password</p>
<p>AT+FTPGETNAME="MTK3.EPO" OK</p>	<p>Set download file name</p>
<p>AT+FTPGETPATH="/" OK</p>	<p>Set download file path</p>
<p>AT+FTPEXTGET=1 OK +FTPEXTGET: 1,0</p>	<p>Download data to local buffer</p>
<p>AT+FTPEXTGET=4,"epo" +FTPEXTGET: 2,27648</p> <p>OK</p>	<p>Ave data to local disk as EPO file</p>
<p>AT+FSL=C:\User\ epo</p> <p>OK</p>	<p>List EPO file</p>
<p>AT+CGNSCHK=3,1 +CGNSCHK: 3,1,27648,61</p> <p>OK</p>	<p>Check EPO file size and validation</p>

<p>AT+CGNSPWR=1 OK</p>	<p>Power on GPS</p>
<p>AT+CGNSAID=31,1,1 OK  +CGNSAID: OK</p>	<p>Send EPO file to GPS  EPO file has been written to GNSS buffer successfully</p>
<p>AT+CGNSINF +CGNSINF: 1,1,20161215045641.000,31.221303,121.355042 ,71.900,0.00,45.1,1,,1.0,1.3,0.8,,10,10,,,36,,  OK</p>	<p>Read GPS location data</p>

SIMCOM CONFIDENTIAL FILE

## APPENDIX

### A Related documents

SN	Document name	Remark
[1]	SIM800 Series_AT Command Manual	
[2]	SIM800 Series_GSM Location_Application Note	
[3]	SIM868 GNSS_Application Note	
[4]	SIM868_NMEA Message Specification	

### B Terms and Abbreviations

Abbreviation	Definition
APN	Access Point Name
URC	Unsolicited Result Code
FTP	File Transfer Protocol
GGA	Global Positioning System Fixed Data
GLL	Geographic Position - Latitude/Longitude
GNSS	Global Navigation Satellite System
GPS	Global Positioning System
AGPS	Assisted GPS
DGPS	Differential Global Positioning System
GPRS	General Packet Radio Service
GSA	GNSS DOP and Active Satellites
GSV	GNSS Satellites in View
HPA	Horizontal Position Accuracy
VPA	Vertical Position Accuracy
GEO-Fence	A geographic area
HDOP	Horizontal Dilution of Precision
HTTP	Hypertext Transfer Protocol
NMEA	National Marine Electronics Association
PDOP	Position Dilution of Precision
PDP	Packet Data Protocol
RMC	Recommended Minimum Specific GNSS Data
VDOP	Vertical Dilution of Precision
VTG	Course Over Ground and Ground Speed
ZDA	Time & Date

**Contact us:**

**Shanghai SIMCom Wireless Solutions Co.,Ltd.**

Address: Building A, SIM Technology Building, No. 633, Jinzhong Road, Shanghai, P.  
R. China 200335

Tel: +86 21 3252 3300

Fax: +86 21 3252 2030

URL: [www.simcomm2m.com](http://www.simcomm2m.com)

SIMCOM CONFIDENTIAL FILE